
## **BAY-LINE®** MARINE SEARCHLIGHTS

# 20" Diameter MODEL 42033 - Series Lever Control

PRODUCT DATA



#### STANDARD MODELS

Model Number	Finish	Dim. A Rod Length Below Base	Dim. B Maximum Roof Thickness	
42033-0160	gray	17"	7"	
42033-0150	gray	23"	13"	

Light is supplied less bulb. See bulb selection data.

## DIMENSIONAL DRAWING 120 2 5/8" DIA. B.C. 11/32" DIA. (3) FOR 5/16" FLATHEAD SCREWS **ESCUTCHEON PLATE** 32" 60 DIM. A 8" DIA. B.C. 11/32" DIA, MOUNTING MAX, ROOF HOLES (6) FOR 5/16" THICKNESS FLAT HEAD SCREWS BASE MOUNTING DIMENSIONS MAXIMUM WIDTH ACROSS TRUNNION = 26"

#### **FEATURES**

Corrosion-resistant cast aluminum construction.

Gray marine lacquer finish over zinc-chromate primer.

Weatherproof drum.

Heat-resistant tempered convex lens set in asbestos gasket and sealing compound.

Escutcheon plate covers and finishes clearance hole in cabin

Single-lever action for quick horizontal and vertical sweep.

360° horizontal sweep and 70° vertical motion.

Horizontal and vertical locking device.

Mogul screw bulb socket.

Precision-formed tempered mirror reflector.

Auxiliary reflector for beam efficiency.

External focusing device.

Hinged door for easy relamping.

Rubber covered wiring cable with water-tight fitting.

Shipping weight: approximately 190 lbs.

#### BULB SELECTION DATA

Mogul Screw Bulb Number	Voltage	Wattage	Service Life (Hours)	Bulb Code
98039-0500	115	1000	50	DPT
98039-0490	115	1500	25	

#### INSTALLATION AND MAINTENANCE

INSTALLATION INSTRUCTIONS: Searchlight should be mounted so base is level. Drill a 1 1/2" clearance hole through roof for outside control rod. Remove bolt for connecting links to rod. Loosen thumbscrew (Key 9A) and set screws (Key 9C) and remove handle (Key 10) and fulcrum (Key 9). Loosen set screws (Key 8A) and thumbscrew (Key 6A). Remove fixed stop (Key 8), sliding stop (Key 7), and escutcheon plate (Key 6).

Mount light in place. After putting sealing compound under base, fasten to roof with (6) 5/16" diameter bolts or wood screws. Replace escutcheon plate, and mount plate to ceiling with thumbscrew facing aft. With light facing forward, place sliding stop (Key 7) over outside control rod and firmly against the escutcheon plate. Place the fixed stop (Key 8) firmly against the sliding stop and, with the stop point facing forward, tighten set screws (Key 8A). Replace handle and fulcrum. Tighten set screws (Key 9C) to firmly fasten fulcrum to outside control rod. Check that all set screws and bolts are tightened properly.

JABSCO PRODUCTS -

### INSTALLATION AND MAINTENANCE (CONT'D.)

WIRING INSTRUCTIONS: Use stranded copper wire. For 110 volt applications, use No. 14 gauge wire for up to 75' from power source. For lengths greater than 75', a heavier gauge Wire should be used. Connect green wire to ground. Wire should be fused for 15 amps.

RELAMPING AND FOCUSING: Loosen thumbscrews (Key 13E) and move dogs away to open door. Unscrew and remove bulb. Clean mirror and auxiliary reflector with a soft, lint-free cloth. Install new bulb. Close door and tighten thumbscrews.

19

2

10E

10D OB

ECRET TRISTER

13A

13E

15

19B

000年年前,

6

4

. 8

Party - Com


1347

12

Adjust focusing with thumbscrew (Key 19A) for desired beam width.

MAINTENANCE: Clean the bulb, lens, auxiliary reflector and main reflector periodically with a soft, lint-free cloth for best efficiency. Lubricate with all-weather grease at grease fitting. Carefully check all bolts and set screws for proper tightness.

### PARTS LIST



number (i.e. key numbers 15A, 15B and 15C should be ordered with the lens, key 15).

# JABSCO PRODUCTS

Marine and Recreation Components Division International Telephone and Telegraph Corporation 1485 Dale Way, Costa Mesa, California 92626

Telephone: (714) 545-8251

