

Pump

| WITH R.V. | P NPT | R | U | C | L | M WITH R.V. | M W/O R.V. | N | S |
|-----------|-------|-------|-----|---------|--------|-------------|------------|-------|-------|
| 10UR | 1 | 7 | 5/8 | 1-15/16 | 6-3/16 | 4-1/16 | 2-1/4 | 2-3/4 | 6-7/8 |
| 15UR | 1-1/4 | 7 | 5/8 | 1-15/16 | 6-3/16 | 4-1/16 | 2-1/4 | 2-3/4 | 6-7/8 |
| 20UR | 1-1/4 | 7 | 5/8 | 1-15/16 | 6-3/16 | 4-1/16 | 2-1/4 | 2-3/4 | 6-7/8 |
| 22UR | 1-1/2 | 7-3/8 | 7/8 | 1-29/32 | 6-5/16 | 4-1/16 | 2-1/4 | 3 | 7-1/8 |
| 30UR | 1-1/2 | 7-3/8 | 7/8 | 1-29/32 | 6-5/16 | 4-1/16 | 2-1/4 | 3 | 7-1/8 |
| 40UR | 1-1/2 | 7-3/8 | 7/8 | 1-29/32 | 6-5/16 | 4-1/16 | 2-1/4 | 3 | 7-1/8 |

Bracket sizes coincide with NEMA motor frame designations

Bracket

| SIZE | D | A | B | E | F | H | G | J |
|------|-------|--------|-------|-------|-------|-------|-----|--------|
| H140 | 3-1/2 | 7 | 2-1/8 | 2-3/4 | 0 | 1/2 | 5/8 | 1-1/2 |
| H182 | 4-1/2 | 9 | 3-1/2 | 3-3/4 | 1-7/8 | 1/2 | 3/4 | 7/8 |
| H213 | 5-1/4 | 10 | 3-1/2 | 4-1/4 | 1-7/8 | 1/2 | 3/4 | 7/8 |
| H254 | 6-1/4 | 12-1/8 | 4-5/8 | 5 | 1-1/2 | 11/16 | 3/4 | 1-1/16 |

