



Model 45960-Series

BULB REPLACEMENT INSTRUCTIONS

For flush mount Floodlight models 45960-Series using replacement bulb kits 18753-0351 (trapezoidal beam) or 18753-0352 (flood beam).

1. Loosen the (4) four bulb adjustment screws, back out at least 1/2".
2. Carefully pry the bulb and rubber boot together out of the light housing (watch the wire length), as far as possible.
3. Remove the bulb from the rubber boot and disconnect the wires.
4. Connect the wires to the new bulb.
5. Lubricate the front lip and groove of the rubber boot lightly with water.
6. Insert the bulb into the rubber boot.
7. Push the bulb (and rubber boot) back into light housing until it is seated.
8. Tighten the (4) four adjustment screws to secure the bulb in the housing and re-set the beam aim.

BEAM AIMING ADJUSTMENT

The Jabsco flush mount floodlight lamp is adjustable up to 7° horizontally and 12° vertically to custom fit to any transom/bulkhead.

To adjust beam up, turn the two (2) top screws in the rubber housing clockwise about the same number of turns each to get the tilt required. Limit adjustment to 25 turns in, on any one (1) screw. The settings may be changed within that range at any time. Turn screws counterclockwise to the original position to re-center the lamp.

To adjust beam down, follow the same procedure using the two (2) bottom screws. To adjust beam to the left or right follow the same procedure using the left or right side screws.

Jabsco



ITT Industries
Engineered for life

U.S.A.
Jabsco
1485 Dale Way, P.O. Box 2158
Costa Mesa, CA 92628-2158
Tel: (714) 545-8251
Fax: (714) 957-0609

UNITED KINGDOM
Jabsco
Bingley Road, Hoddesdon
Hertfordshire EN11 0BU
Tel: +44 (0) 1992 450145
Fax: +44 (0) 1992 467132



CANADA
Fluid Products Canada
55 Royal Road
Guelph, Ontario N1H 1T1
Tel: (519) 821-1900
Fax: (519) 821-2569

JAPAN
NHK Jabsco Company Ltd.
3-21-10, Shin-Yokohama
Kohoku-Ku, Yokohama, 222
Tel: 045-4758906
Fax: 045-475-8908

GERMANY
Jabsco GmbH
Oststrasse 28
22844 Norderstedt
Tel: +49-40-53 53 73 -0
Fax: +49-40-53 53 73 -11