

50 HERTZ, 2 X 1.5 X 6.3 FLG

WELDED STAINLESS STEEL

D236JM182


DRAWING DEPICTS 182JM 5HP ODP MOTOR

MOTOR DIMENSIONS

NEMA JM FRAME 3 PHASE 2900 RPM


HP	Type	Frame	D	E	F	O	AB	BG	L	MH
2	ODP	JM145	3.50	2.75	2.00	6.72	5.87	5.25	4.97	0.34
3	ODP	JM182	4.50	3.75	2.25	8.56	6.70	5.75	6.25	0.41
5	ODP	JM184	4.50	3.75	2.25	8.56	6.70	6.25	6.15	0.41
2	TEFC	JM182	4.50	3.75	2.25	8.85	7.57	5.01	7.14	0.41
3/5	TEFC	JM184	4.50	3.75	2.25	9.34	7.57	5.00	7.76	0.41

Dimensions are the next larger 60Hz motor derated for 50HZ operation.



ALL DIMENSIONS IN INCHES.

DRAWING REPRESENTS APPROXIMATE PUMP DIMENSIONS. AUTOCAD DRAWING TO SCALE AVAILABLE FROM FACTORY



23675DP

D236JM182
2362900

236

JM

2362900JM
81.001.823 M19

50 Hertz Pump & Motor Data

A 3-phase 50 Hertz Motorpump™ can be obtained in several ways. The most common options are listed below:

1. Most 60 Hz pumps available from Scot Pump can be operated on a 3-phase 50 Hz 190/380V power. However, when operated on 50 Hz power, the speed is reduced by approximately 20%, and a significant reduction in performance is realized. The charts below indicate these reductions in performance.
2. Pumps will produce the performance indicated in the performance curves when operated on 50 Hz power. The motors for these selections can be obtained through *derated 60 Hz motors* and *wound 50 Hz motors* (see below).

Contact factory for 1 Phase applications.

Derated 60 Hz Motors

The most common practice and readily available method of obtaining a 50 Hz motor is by using the next larger 60 Hz motor and derating it to the desired horsepower on 50 Hz. We will require the country the motor is being exported to, frequency in hertz and specific voltage to ensure that a nameplate with applicable efficiency and country markings (if required) is supplied. In utilizing this practice, service factors may be derated to 1.0. Please contact the factory for approval of the rating for your specific application.

Wound 50 Hz Motors

Specially wound 50 Hz motors are available. These motors are not normally a stock item and require an extended lead time.

The impeller and horsepower combination sized (taking the reduction in speed into consideration) may not be suitable for operation on 60 Hz power. The increase in speed, performance and load may overload the system and the electric motors. **Pumps sized for 50 Hz operation SHOULD NOT be tested on 60 Hz.**


60 Hz Pump on 50 Hz Power		
No Impeller Change		
50 Hz	60 Hz	Factor
GPM =	GPM x	0.829
Head =	Head x	0.687
BHP =	HP x	0.569

To Size 60 Hz Pump Using 50 Hz Data,		
Obtain 60 Hz Data As Follows:		
60 Hz	50 Hz	Factor
GPM =	GPM x	1.2
Head =	Head x	1.45
BHP =	HP =	$\frac{\text{GPM} \times \text{Head} \times \text{SG of}}{3960 \times \text{Eff}}$

Change of Speed (RPM)		
	How Varies:	Examples
GPM	Directly	Double RPM = (2)(RPM) = (2)(GPM) Triple RPM = (3)(RPM) = (3)(GPM)
Head	Square	Double RPM = (2)(RPM) = (2) ² = (2)(2) = (4)(Head) Triple RPM = (3)(RPM) = (3) ² = (3)(3) = (9)(Head)
BHP	Cube	Double RPM = (2)(RPM) = (2) ³ = (2)(2)(2) = (8)(BHP) Triple RPM = (3)(RPM) = (3) ³ = (3)(3)(3) = (27)(BHP)

Change of Impeller Diameter (Dia.)		
	How Varies:	Examples
GPM	Directly	Double Dia. = (2)(Dia.) = (2)(GPM) Triple Dia. = (3)(Dia.) = (3)(RPM)
Head	Square	Double Dia. = (2)(Dia.) = (2) ² = (2)(2) = (4)(Head) Triple Dia. = (3)(Dia.) = (3) ² = (3)(3) = (9)(Head)
BHP	Cube	Double Dia. = (2)(Dia.) = (2) ³ = (2)(2)(2) = (8)(BHP) Triple Dia. = (3)(Dia.) = (3) ³ = (3)(3)(3) = (27)(BHP)


Pump 236 • 304SS • JM Frame • 2900 RPM



KEY NO.	PART NAME	PUMP 236
1	CASE, 304SS, 2.0 x 1.5, NPT	137.001.457
2	IMPELLER, STAINLESS, ENCLOSED, 7/8" KEYED:	
	4.80" DIA	137.001.474
	5.80" DIA	137.001.473
	6.30" DIA	137.001.458
4	MOTOR, JM140/180	See 60HZ Chart
11	COVER, 304SS	137.001.459
14*	SHAFT SLEEVE, 304SS	137.001.476
26*	IMPELLER RETAINER, 304SS	118.000.111A
32*	KEY, 303SS	102.000.102
38*	O-RING, SHAFT, BUNA	116.000.117
40*	FLINGER, 304SS	104.000.165
71	DISC, IRON	137.001.435
73*	GASKET, CASE, BUNA	137.001.121
89*	1-1/8" SEALS	
	TYPE 21, BN-CARB/CM	137.001.079
	TYPE 21, VN-CARB/CM	137.001.324
	TYPE 21, VN-CARB/SIL	137.001.669
	TYPE 21, VN-SIL/SIL	137.001.546
	TYPE 21, EPDM-CARB/SIL	137.001.490
89A	SEAL RETAINER, STAINLESS	137.001.477A
--	REPAIR KITS:	
	BN-CARB/CM SEAL	118.000.605
	VN-CARB/CM SEAL	118.000.605A
	VN-CARB/SIL SEAL	118.000.605D
	VN-SIL/SIL SEAL	118.000.605B
	EPDM-CARB/SIL SEAL	118.000.605C

* DENOTES COMPONENTS INCLUDED IN REPAIR KIT.

Pump 236 • 304SS • JM Frame • 2900 RPM



CONSTRUCTION OPTIONS		
KEY	PART NAME	STANDARD FITTED
1	Case	304SS
2	Impeller	304SS
11	Cover	304SS
14	Sleeve	304SS
26	Retainer Assembly	304SS
32	Key	303SS
38	Gasket Shaft	BUNA
40	Flinger	304SS
71	Motor Disc	Cast Iron
73	Gasket, Case	Buna
89	Seal Assembly	BN-CARB/CM
89A	Seal Retainer	304SS

E236JM

D11

C2362900JM